Une fois connecté à l'interface avec l'utilisateur admin (apc). Vous avez normalement cette page:

Schne GEI	ectri	C UPS	S Network Mana rt-UPS Application	gement C	ard 3		♥ No Alarms 9 apc English 쿄 Log Off Help ★
Home S	tatus 👻	Control 🗸	Configuration 🗸	Tests 👻	Logs 🗸	About 👻	
Home							
Model Smart-UPS 75 No Alarms • UPS is	i0 Present online.					Location Unknown	
Environme Vo Alarms	nt Present						
Recent De	evice Ev	ents					
Date	Time	Event					
03/02/2021	11:03:26	Environme	ent: Restored the loca	al network ma	anagement i	interface-to-integrated Envi	ronmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	11:03:26	UPS: Rest	ored the local netwo	rk managem	ent interface	e-to-UPS communication.	
03/02/2021	10:54:40	Environme	ent: Restored the loca	al network ma	anagement i	interface-to-integrated Envi	ronmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	10:54:40	UPS: Rest	cored the local netwo	rk managem	ent interface	e-to-UPS communication.	
03/02/2021	09:41:05	UPS: The	output power is turne	ed off.			
							More Events >
nowledge Base	Schneider	Electric Proc	duct Center Schneid	ler Electric D	ownloads		© 2019, Schneider Electric. All rights reserved. Site Map Updated: 03/02/2021 at 11:03 (10.2.0.7)

Pour configurer SNMP, allez sur l'onglet "Configuration" ensuite dans le menu "Network", puis "SNMPv1" et ensuite cliquez sur "Access".



UPS Network Management Card 3 Smart-UPS Application

🤉 apc | English 💷 Log Off | Help | 🖈

V No Alarms

Home S	tatus 👻	Control -	Configuration -	Tests	 Logs 	Abo	lt ▼
Home		Outlet Groups Power Settings					
Model Smart-UPS 75 Vo Alarms • UPS is	Model Smart-UPS 750 On Alarms Present • UPS is online.		Shutdown UPS Self-Test Schedule				Location Unknown
Environme Vo Alarms	Environment So No Alarms Present		Scheduling Firmware Update PowerChute Clients	s			
Recent De	Recent Device Events		Universal I/O Security	•			
Date	Time	Event	Network	•	Summary		
03/02/2021	11:03:26	Environme	Notification	•	TCP/IP	•	e-to-integrated Environmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	11:03:26	UPS: Rest	General	•	Port Speed		S communication.
03/02/2021	10:54:40	Environme.	Logs	•	DNS Web	*	e-to-integrated Environmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	10:54:40	UPS: Resto	red the local network	mar	Console	+	S communication.
03/02/2021	09:41:05	UPS: The o	utput power is turned	off.	SNMPv1	•	Access
					SNMPv3 Modbus	•	Access Control More Events >
nowledge Base Schneider Electric Product Center Schneider Ele			BACnet FTP server		© 2019, Schneider Electric. All rights reserved. Site Map Updated: 03/02/2021 at 11:04 (10.2.0.7)		

La page suivante apparaît, cochez la case "enable" et ensuite sur "Apply" pour activer SNMPV1.



Ensuite, il faut configurer les managers SNMP et la communauté.

Allez sur l'onglet "Configuration" ensuite dans le menu "Network", puis "SNMPv1" et ensuite cliquez sur "Access Control".

3/5

Schneider Gelectric

UPS Network Management Card 3 Smart-UPS Application

♥ No Alarms 9 apc | English | II Log Off | Help | ★

Home S	tatus 👻	Control 👻	Configuration - Test	s 👻 Logs 👻	About +
Home			Outlet Groups Power Settings		
Model Smart-UPS 750 No Alarms Present • UPS is online. Environment No Alarms Present		Shutdown UPS Self-Test Schedule	Location Unknown		
		Scheduling Firmware Update PowerChute Clients			
Recent De	Recent Device Events		Universal I/O		
Date	Time	Event	Network	Summary	
03/02/2021	11:03:26	Environme	Notification	TCP/IP	• e-to-integrated Environmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	11:03:26	UPS: Rest	General •	Port Speed	5 communication.
03/02/2021	10:54:40	Environme.	Logs •	DNS Web	e-to-integrated Environmental Monitor (Universal I/O at Port 2) communication.
03/02/2021	10:54:40	UPS: Resto	red the local network mar	Console	, 5 communication.
03/02/2021	09:41:05	UPS: The o	utput power is turned off.	SNMPv1 SNMPv3 Modbus	Access Access Control More Events >
Knowledge Base Schneider Electric Product Center Schneider Ele			uct Center Schneider Ele	BACnet FTP server	© 2019, Schneider Electric. All rights reserved. Site Map Updated: 03/02/2021 at 11:04 (10.2.0.7)

La page suivante apparaît:

The system needs to reboot for a configuration change to take effect.						
Schneider Gelectric	UPS Network Management Card 3 Smart-UPS Application	♥ No Alarms 9 apc English 코 Log Off Help ★				
Home Status - Control - Configuration - Tests - Logs - About -						
Configure SNMPv1 Access Control						
Access Control						

Community Name	NMS IP/Host Name	Access Type
Community Name 1	0.0.0.0	Disabled
Community Name 2	0.0.0.0	Disabled
Community Name 3	0.0.0.0	Disabled
Community Name 4	0.0.0.0	Disabled

Knowledge Base | Schneider Electric Product Center | Schneider Electric Downloads

© 2019, Schneider Electric. All rights reserved. Site Map | Updated: 03/02/2021 at 11:05 (10.2.0.7)

Cliquez sur "Community Name 1", pour configurer la première communauté:



Rentrez votre communauté (ici: public) et l'adresse IP de votre Esia ou Unity. Concernant les accès un accès "read" suffit et pour terminer vous pouvez cliquer sur "Apply". Et vous retournez à la page précédente

The system needs to reboot for a configuration change to take effect.						
Schneider Electric UPS Network Manage	ment Card 3	♥ No Alarms 9 apc English 과 Log Off Help ★				
Home Status - Control - Configuration - 1	īests ▼ Logs ▼ About ▼					
Configure SNMPv1 Access Control						
Access Control						
Community Name	NMS IP/Host Name	Access Type				
public	192.168.1.1	Read				
Community Name 2	0.0.0.0	Disabled				
Community Name 3	0.0.0.0	Disabled				
Community Name 4	0.0.0.0	Disabled				

Knowledge Base | Schneider Electric Product Center | Schneider Electric Downloads

© 2019, Schneider Electric. All rights reserved. Site Map | Updated: 03/02/2021 at 11:05 (10.2.0.7)

Vous remarquerez qu'il y a un bandeau bleu qui est apparu, il dit qu'il faut redémarrer l'interface de management. Pour ce faire il faut aller dans le menu "Control", ensuite dans "network" et "Reset/reboot".

2025/05/03 01:56	5/5	Activation SNMP sur un UPS APC
The system needs to reboo	ot for a configuration change to take effect.	×
Schneide Gelectr	UPS Network Management Card 3 Smart-UPS Application	♥ No Alarms ೨ apc English 과 Log Off Help ★
Home Status 🗸	Control	
Configure SNN	UPS Outlet Groups	
SNMPv1 Access	Security Network Reset/Reboot	
Apply Cancel		
Knowledge Base Schne	ider Electric Product Center Schneider Electric Downloads	© 2019, Schneider Electric. All rights reserved. Site Map Updated: 03/02/2021 at 10:30 (10.2.0.7)

Laissez coché "Reboot Management Interface" et cliquez sur "Apply"



Si vous avez connecté un capteur de température APC, vous pouvez ajouter le service 'CHECK_SNMP_APC_SENSORS' qui ne se trouve pas dans le pattern par défaut des UPS.

From: https://wiki.esia-sa.com/ - Esia Wiki
Permanent link: https://wiki.esia-sa.com/snmp_ups_apc
Last update: 2023/02/10 10:25