

# Prerequisites

## By solution

### ESIA UNITY

To use the ESIA Unity solution in the best possible conditions, you need the following:

- Access to your ESIA interface
- At least one ESIA Unity box connected to the network
- Activate SNMP on all the equipment you wish to monitor.
- Ensure that ports 80 and 443 are open

### ESIA GALAXY

To use the ESIA Galaxy solution, the software must be installed on a server (physical or virtual) with the following configuration:

- 4 cores (64 bits)
- 4 GB RAM
- 30 GB of disk space
  - /var: 10GB
  - /usr: 10GB
  - /: 10GB
- 

**Debian 12 Bookworm** 64-bit (amd64) [Download](#)

**This is the MINIMUM configuration for standard use of ESIA Galaxy.** Depending on your needs (number of services), we may recommend a higher configuration. Please contact our technical department for more information.

If the Galaxy is used as a satellite for an Infinity or Universe server, these servers must have HTTPS access to the Galaxy server.

### ESIA INFINITY

To use the ESIA Infinity solution, the software must be installed on a server (physical or virtual) with the following configuration:

- 8 cores (64-bit)
- 8 GB RAM

- 50 GB of disk space
  - /var: 20GB
  - /usr: 20GB
  - /: 10GB
- **Debian 12 Bookworm** 64-bit (amd64) [Download](#)

**This is the RECOMMENDED configuration for standard use of ESIA Infinity.** Depending on your needs (number of services), we may recommend a higher configuration. Please contact our technical department for more information.

## ESIA MERCURY - HEIMDALL

To use the ESIA Universe solution, you need to install the software on a server (physical or virtual) with the following configuration:

- 4 cores (64 bits)
- 8 GB RAM
- 50 GB of disk space
  - /var: 20GB
  - /usr: 20GB
  - /: 10GB

- **Debian 12 Bookworm** 64-bit (amd64) [Download](#)

**This is the RECOMMENDED configuration for standard use of ESIA Mercury.** Depending on your needs (number of services), we may recommend a higher configuration. Please contact our technical department for more information.

## Svalinn probe

To use Svalinn, you can either :

- Order a Svalinn box
- Install the probe on a server (physical or virtual)

This probe will be connected to your Esia.

If you wish to install the probe on a virtual server, your server must have the following configuration:

- 2 cores (64 bits)
- 2 GB RAM
- 15 GB disk space

- **Debian 12 Bookworm** 64-bit (amd64) [Download](#)

**This is the RECOMMENDED configuration for standard use.** Depending on your needs (number of services), we may recommend a higher configuration. Please contact our technical department for more information.

After installation, you will need a serial number, which we will supply to you. This serial number is used to identify the Box. You can send an email to [support@esia-sa.com](mailto:support@esia-sa.com) with the following information:

- Is the server already known to Esia (are there already linked Svalinn/Unity boxes)?
- Its hostname
- Its url or public ip https (port 2080) or private ip (if the box is on the same site as the Esia server)

## Network feeds (for all)

For installation, updates and modifications to Esia licences, your server must have the following network access:

On ports **80** and **443** (input and output on the Internet) :

- Official Debian repositories (choice of one or the other)

French repositories : **ftp.fr.debian.org/debian**

Belgian repositories : **ftp.be.debian.org/debian**

- ESIA repositories : **stable.repository.esia-sa.com**


- Esia license validation server : **licence.esia-sa.com**

- (Esia Unity/Mercury only) Unity connection server : **infogesa.esia-sa.com** and **infogesa.esia-network.com**

At the port **22** (inbound from your local network to the Esia server) for SSH administration  
(Esia Unity/Mercury only) port **2080** (input from internet)

From:

<https://wiki.esia-sa.com/> - **Esia Wiki**



Permanent link:

<https://wiki.esia-sa.com/en/intro/prerequis>

Last update: **2025/11/21 11:40**